



## DALI dimmable DT8 CCT driver 220-240V - Output 6-54V DC - 500-1500mA - 65 W

### Ref. SRP-2309N-65CCT500-1500

DALI dimmable 220-240V 65W driver, converts alternating current into direct current to power LED CCT luminaires such as LED panels, downlights and ceiling lights. It offers precise dimming from 0.01% to 100%, no flicker, high power factor, and energy efficiency. It incorporates protection against short circuit and overload.

### Datos del producto

Nominal Voltage (V)	220 - 240 V/AC
Dimensions (mm) LxLxh	123.9 x 78.8 x 30
Use Outdoor	No
IP	IP20
Certificates	CE, ROHS
Warranty	According to legal guarantee: 2 years
Maximum power (W)	65
Colour control	CCT
Output voltage (V)	6-54V
Output current mA	500-1500mA

