




WIRING DIAGRAM




Note:

1. Connecting with green terminal (DMX-AMP) or an extra amplifier will be needed when more than 32 LEDs are connected, or use switching signal line, signal amplification should not be more than 3 times continuously.
2. If the visual effect occurs because of longer signal line or bad line quality, please try to connect 0.25W 50-120Ω terminal resistor at the end of each DMX signal line.

Αποκωδικοποιητής DMX512 12-24V DC - 5A/κανάλι - 12 κανάλια - Οθόνη OLED

Ref. SK-D12A

Ο αποκωδικοποιητής DMX512 είναι μια συσκευή ελέγχου φωτισμού LED με 12 κανάλια εξόδου, το καθένα με μέγιστο ρεύμα 5A. Είναι συμβατός με τάσεις εισόδου 12-24V. Ενσωματώνει οθόνη OLED και πλήκτρα για την επιλογή της αρχικής διεύθυνσης DMX. Χρησιμοποιεί σήμα εισόδου DMX512 και παρέχει σήμα εξόδου PWM για ομαλό έλεγχο του φωτισμού.



Product data

Onomastikh tash (V)	12-24V DC
Diastaseis (mm) LxIhx	246 x 116 x 38,5
Exoterikí chrísi	ochi
IP	IP20
Pistopoihtika	EK, ROHS
Egyhsh	5 xronia
Tash exodou (V)	12 - 24
Arithmos kanaliwn	12
Megisto reuma (A)	5A/kanali

